

Prestige 642 Router

Menu 1 - General Setup

System Name= P642
Location=
Contact Person's Name=

Route IP= **No**
Route IPX= No
Bridge= **Yes**

Die IP Adresse von Menu 3.2 ist irrelevant

Menu 4 - Internet Access Setup

ISP's Name= ChangeMe
Encapsulation= **RFC 1483**
Multiplexing= LLC-based
VPI #= 8
VCI #= 35
Service Name= N/A
My Login= N/A
My Password= N/A
Single User Account= **No**
IP Address Assignment= N/A
IP Address= N/A
ENET ENCAP Gateway= N/A

Menu 11.1 - Remote Node Profile

Rem Node Name= ChangeMe
Active= Yes

Encapsulation= RFC 1483
Multiplexing= LLC-based

Incoming:

Rem Login= N/A
Rem Password= N/A

Outgoing:

My Login= N/A
My Password= N/A
Authen= N/A

Route= **None**
Bridge= **Yes**

Edit PPP Options= N/A
Rem IP Addr= N/A
Edit IP/IPX/Bridge= No

Session Options:
Edit Filter Sets= No
PPPoE Idle Timeout(sec)= N/A
PPPoE Service Name= N/A
Schedule Sets= N/A